



Motor size	No- load electrical power		No- load current [A]					
	[kW]	cos phi	220V	230V	380V	400V	415V	500V
<b>BB</b>	0.3	0.33	2.7	2.5	1.3	1.5	1.8	1.2
<b>BD</b>	0.4	0.31	3.4	3.6	1.7	1.9	2.5	1.5
<b>BE</b>	0.4	0.31	3.4	3.6	1.7	1.9	2.5	1.5
<b>BH</b>	0.7	0.28	6.0	5.7	3.5	3.3	3.2	2.6
<b>BJ</b>	0.8	0.29	7.3	7.0	4.2	4.0	3.8	3.2
<b>BR</b>	0.9	0.24	12.2	11.6	5.7	6.7	8.9	5.3
<b>BZ</b>	0.9	0.24	10.4	9.9	5.1	5.7	6.7	4.6
<b>DA</b>	0.2	0.25	2.1	2.0	1.2	1.1	1.1	0.9
<b>DC</b>	0.3	0.18	3.1	3.0	1.5	1.7	2.0	1.4
<b>DD</b>	0.3	0.18	3.1	3.0	1.5	1.7	2.0	1.4
<b>DG</b>	0.5	0.17	7.6	7.3	4.4	4.2	4.0	3.3
<b>DG-E/C</b>	0.6	0.14	10.9	10.4	6.3	6.0	5.8	4.8
<b>DJ</b>	0.6	0.14	10.9	10.4	6.3	6.0	5.8	4.8
<b>DL</b>	0.6	0.14	10.9	10.4	6.3	6.0	5.8	4.8
<b>DO</b>	0.8	0.14	11.2	10.7	6.5	6.2	6.0	4.9
<b>DU</b>	0.8	0.14	14.7	14.0	8.5	8.1	7.8	6.5
<b>DZ</b>	0.8	0.11	19.5	18.7	11.3	10.7	10.3	8.6
<b>FE</b>	0.3	0.16	5.0	4.8	2.9	2.8	2.7	2.2
<b>FH</b>	0.9	0.21	11.1	10.6	6.4	6.1	5.9	4.9
<b>FR</b>	0.9	0.18	13.0	12.4	7.5	7.2	6.9	5.7
<b>FZ</b>	1.3	0.16	21.7	20.8	12.6	11.9	11.5	9.6
<b>JE</b>	1.8	0.20	23.5	22.4	13.6	12.9	12.5	10.3
<b>JG</b>	2.9	0.28	19.0	18.2	11.0	10.5	10.1	8.4
<b>JL</b>	4.0	0.37	28.3	27.1	16.4	15.6	15.0	12.5
<b>LD</b>	1.2	0.10	31.1	29.7	18.0	17.1	16.5	13.7
<b>LF</b>	1.0	0.11	23.8	22.8	13.6	13.0	12.6	10.5
<b>LI</b>	1.6	0.09	45.4	43.4	26.3	25.0	24.1	20.0
<b>LL</b>	3.0	0.13	52.2	59.4	36.0	34.2	33.0	27.4

Note: A deviation of 10% for power and current is acceptable